# Anomalous scattering of light by slit structures in metallic slabs

#### Hai Zhang

#### Department of Mathematics, HKUST

Workshop on Qualitative and Quantitative Approaches to Inverse Scattering Problems Sep 25, 2018

Joint work with Junshan Lin, Auburn University, USA

イロト イポト イヨト イヨ

# Extraordinary Optical Transmission Through a Small Hole Array

T. W. Ebbessen *et al*, Nature (1998)

Size of each hole: 150 nm, metal thickness: 300 nm, skin depth: 30nm





Classical Bethe theory for diffraction by a small hole





# Subsequent Development in Extraordinary Optical Field Enhancement

F. J. Garcia-Vidal *et al*, Rev. Mod. Phy. (2010) S. Rodrigo, F. León-Pérez, L. Martín-Moreno, Proceedings of the IEEE (2016)



Applications: Near-field optical imaging, biosensing, novel optical devices....

Surface plasmonic resonances in noble metals



 Non-plasmonic resonances (e.g., resonances induced by the geometry of the structure)



Non-resonant enhancement,....

- There has been a long debate on the interpretation of enhancement effects. For instance, surface plasmonic resonances strengthen or inhibit the enhancement? interplay between different enhancement mechanisms?
- Other questions: How large is the field enhancement and at what frequencies?
- Quantitative analysis of the field enhancement would be desirable!

#### Focus on a Prototype Structure: Narrow Slits



Field enhancement for slit structures in perfect conducting (PEC) metals:

• Single slit and an array of slits.

#### Related work:

- E. Bonnetier and F. Triki (2010): Resonances for a subwavelength cavity.
- Gao, Li, Yuan (2017): field enhancement for a subwavelength cavity.
- High transmission for the periodic structures: G. Bouchitté, B. Schweizer, G. Kriegsmann, and many others in physics literatures.

#### Electromagnetic Field Enhancement in a Single PEC Slit



Transmission with metal thickness = 1, gap size = 0.02.

#### Resonant effect

Y. Takakura (2001), J. Sambles *et al* (2002), F. Garcia-Vidal, *et al* (2004), R. Gordon (2006) ···

#### Non-resonant effect

Experiments: D-S. Kim (2009), S-H. Oh (2014)

# Scattering Problem II



- Normalization:  $\ell = 1$ .
- The exterior domain:  $\Omega_{\mathcal{E}} = \Omega_+ \cup \Omega_- \cup S_{\mathcal{E}}$ .
- TM polarization: the incident magnetic field  $H^i = (0, 0, u^i)$ , where  $u^i = e^{ikd \cdot x}$ ,  $k = \omega/c$ .
- The total field  $u_{\mathcal{E}} = u^i + u^r + u^s_{\mathcal{E}}$  in  $\Omega^+$ , and  $u_{\mathcal{E}} = u^s_{\mathcal{E}}$  (transmitted wave) in  $\Omega^-$ .
- The scattering problem:

$$\begin{split} \Delta u_{\mathcal{E}} + k^2 u_{\mathcal{E}} &= 0 & \text{in } \Omega_{\mathcal{E}}, \\ \frac{\partial u_{\mathcal{E}}}{\partial v} &= 0 & \text{on } \partial \Omega_{\mathcal{E}}. \\ \lim_{r \to \infty} \sqrt{r} \left( \frac{\partial u_{\mathcal{E}}^s}{\partial r} - ik u_{\mathcal{E}}^s \right) &= 0, \quad r = |x|, \\ &= 0 \quad \text{in } n = 0 \quad$$



• Fact: The scattering problem attains a unique solution if  $\text{Im } k \ge 0$ .

#### Defintion

The *scattering resonances* are the poles of the scattering operator when continued meromorphically to the whole complex plane.

• Field enhancement at resonant frequencies:  $O\left(\frac{1}{|k|}\right)$ 

$$\left(\frac{1}{|k-k_{res}|}\right).$$

# Integral Equation Formulation



Integral equation formulation:

$$\begin{cases} \int_{\Gamma_{\varepsilon}^{+}} g^{e}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} + \int_{\Gamma_{\varepsilon}^{+} \cup \Gamma_{\varepsilon}^{-}} g^{i}_{\varepsilon}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} = -(u^{i} + u^{r}), \quad \text{on } \Gamma_{\varepsilon}^{+}, \\ \int_{\Gamma_{\varepsilon}^{-}} g^{e}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} + \int_{\Gamma_{\varepsilon}^{+} \cup \Gamma_{\varepsilon}^{-}} g^{i}_{\varepsilon}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} = 0, \quad \text{on } \Gamma_{\varepsilon}^{-}. \end{cases}$$

• Boundary integral equations after scaling  $(x_1 = \varepsilon X, y_1 = \varepsilon Y, X, Y \in (0, 1))$ :

$$\begin{bmatrix} T^e + T^i & \tilde{T}^i \\ \tilde{T}^i & T^e + T^i \end{bmatrix} \begin{bmatrix} \varphi_1 \\ \varphi_2 \end{bmatrix} = \begin{bmatrix} f/\varepsilon \\ 0 \end{bmatrix}$$

where  $T^e$ ,  $T^i$ , and  $\tilde{T}^i$  are the integral operators with kernels  $G^e_{\mathcal{E}}$ ,  $G^i_{\mathcal{E}}$  and  $\tilde{G}^i_{\mathcal{E}}$ ,  $\varphi_1(X) := -\partial_V u_{\mathcal{E}}(\mathcal{E}X, 1)$ , and  $\varphi_2(X) := -\partial_V u_{\mathcal{E}}(\mathcal{E}X, 0)$ .

#### Asymptotic Expansions for the Integral Operators

Asymptotic expansions of the kernels:

$$\begin{split} G^{e}_{\varepsilon}(X,Y) &= \frac{1}{\pi} \left[ \ln \varepsilon + \ln k + \gamma_{0} \right] + \frac{1}{\pi} \ln |X - Y| + O((\varepsilon |X - Y|)^{2} \ln(\varepsilon |X - Y|); \\ G^{i}_{\varepsilon}(X,Y) &= \frac{\cot k}{k\varepsilon} + \frac{2\ln 2}{\pi} + \frac{1}{\pi} \left[ \ln \left( \left| \sin \left( \frac{\pi (X + Y)}{2} \right) \right| \right) + \ln \left( \left| \sin \left( \frac{\pi (X - Y)}{2} \right) \right| \right) \right] \\ &+ O(k^{2} \varepsilon^{2}); \\ \tilde{G}^{i}_{\varepsilon}(X,Y) &= \frac{1}{(k \sin k)\varepsilon} + O\left( e^{-1/\varepsilon} \right). \end{split}$$

• Asymptotic expansions of the integral operators:

$$\begin{bmatrix} T^e + T^i & \tilde{T}^i \\ \tilde{T}^i & T^e + T^i \end{bmatrix} = \begin{bmatrix} \beta & \tilde{\beta} \\ \tilde{\beta} & \beta \end{bmatrix} P + K\mathbb{I} + \begin{bmatrix} K_{\infty} & \tilde{K}_{\infty} \\ \tilde{K}_{\infty} & K_{\infty} \end{bmatrix} =: \mathbb{P} + \mathbb{L}.$$

• The system of integral equations becomes  $(\mathbb{P} + \mathbb{L}) \varphi = \mathbf{f}$ .

#### **Resonant Effect I: Resonance Condition**

- Look for *k* such that  $(\mathbb{P} + \mathbb{L})\varphi = 0$  attains non-trivial solutions.
- The operator equation reduces to

$$(\mathbb{M} + \mathbb{I}) \left[ egin{array}{c} \langle oldsymbol{\varphi}, \mathbf{e}_1 
angle \\ \langle oldsymbol{\varphi}, \mathbf{e}_2 
angle \end{array} 
ight] = 0,$$

where  $\mathbf{e}_1 = [1,0]^T$  and  $\mathbf{e}_2 = [0,1]^T$ , and the matrix

$$\mathbb{M} = \left( \beta \mathbb{I} + \tilde{\beta} \begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} \right) \cdot \left[ \begin{array}{cc} \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_1 \rangle & \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_2 \rangle \\ \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_2 \rangle & \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_1 \rangle \end{array} \right]$$

 $\bullet$  The eigenvalues of  $\mathbb{M}+\mathbb{I}$  are given by

$$\begin{split} \lambda_1(k,\varepsilon) &= 1 + (\beta(k,\varepsilon) + \tilde{\beta}(k,\varepsilon)) \left( \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_1 \rangle + \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_2 \rangle \right), \\ \lambda_2(k,\varepsilon) &= 1 + (\beta(k,\varepsilon) - \tilde{\beta}(k,\varepsilon)) \left( \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_1 \rangle - \langle \mathbb{L}^{-1} \mathbf{e}_1, \mathbf{e}_2 \rangle \right). \end{split}$$

#### Resonance condition

The resonances are the roots of  $\lambda_1(k,\varepsilon) = 0$  or  $\lambda_2(k,\varepsilon) = 0$ .

# Resonant Effect II: Asymptotic Expansions for Resonances



#### Theorem

The following asymptotic expansions hold for the resonances of the scattering problem:

$$\begin{aligned} k_{m,1} &= (2m-1)\pi + 2(2m-1)\pi \left[ \frac{1}{\pi}\varepsilon\ln\varepsilon + \left( \frac{1}{\alpha} + \frac{1}{\pi}(2\ln2 + \ln((2m-1)\pi) + \gamma_0) \right)\varepsilon \right] \\ &+ O(\varepsilon^2\ln^2\varepsilon), \\ k_{m,2} &= 2m\pi + 4m\pi \left[ \frac{1}{\pi}\varepsilon\ln\varepsilon + \left( \frac{1}{\alpha} + \frac{1}{\pi}(2\ln2 + \ln(2m\pi) + \gamma_0) \right)\varepsilon \right] + O(\varepsilon^2\ln^2\varepsilon), \\ \text{for } m &= 1, 2, 3, \cdots, \text{ and } m\varepsilon \ll 1. \text{ Here } \alpha = \langle K^{-1}1, 1 \rangle, \gamma_0 &= c_0 - \ln 2 - i\pi/2, \text{ and } c_0 \end{vmatrix}$$

for  $m = 1, 2, 3, \dots$ , and  $m\varepsilon \ll 1$ . Here  $\alpha = \langle K^{-1}1, 1 \rangle$ ,  $\gamma_0 = c_0 - \ln 2 - i\pi/2$ , and  $c_0$  is the Euler constant.

**Remark** The imaginary part of each resonance has an order of  $O(\varepsilon)$ .

# Field Enhancement at Resonant Frequencies: In the Slit



The wave field inside the slit adopts the following expansion at the odd and even resonances respectively:

$$u_{\varepsilon}(x) = \frac{1}{\varepsilon} \cdot \frac{2i}{k\sin(k/2)} \cdot \cos(k(x_2 - 1/2)) + O(\ln^2 \varepsilon)$$

and

$$u_{\varepsilon}(x) = -\frac{1}{\varepsilon} \cdot \frac{2i}{k\cos(k/2)} \cdot \frac{\sin(k(x_2 - 1/2))}{\sin(k(x_2 - 1/2))} + O(\ln^2 \varepsilon).$$

(ロトメ@トメミトメミト ヨーのへの

#### Non-resonant Enhancement at Low Frequencies I



• Expand the wave field in the slit as the sum of wave-guide modes:

$$u_{\varepsilon}(x) = a_0 \cos kx_2 + b_0 \cos k(1 - x_2) + \sum_{m \ge 1} \left[ a_m \exp\left(-k_2^{(m)} x_2\right) + b_m \exp\left(-k_2^{(m)}(1 - x_2)\right) \right] \cos \frac{m\pi x_1}{\varepsilon}$$

where  $k_2^{(m)} = \sqrt{(m\pi/\varepsilon)^2 - k^2}.$ 

#### Theorem

No significant magnetic field enhancement is gained. However, the electric field  $|E_{\mathcal{E}}| \sim O(1/k)$  or  $|E_{\mathcal{E}}| \sim O(1/(k\ell))$  if  $\ell \neq 1$ .

## Scattering by A Periodic Array of PEC Slits



- The scattering problem:  $\Delta u_{\varepsilon} + k^2 u_{\varepsilon} = 0$  in  $\Omega_{\varepsilon}$  and  $\partial_{v} u_{\varepsilon} = 0$  on  $\partial \Omega_{\varepsilon}$ .
- Look for quasi-periodic solutions such that  $u_{\varepsilon}(x_1 + d, x_2) = e^{i\kappa d}u_{\varepsilon}(x_1, x_2)$ .
- Outgoing radiation condition: the scattered field

$$u_{\varepsilon}^{s}(x_{1},x_{2})=\sum_{n=-\infty}^{\infty}u_{n}^{s,\pm}e^{i\kappa_{n}x_{1}\pm i\zeta_{n}x_{2}}\quad\text{in }\Omega^{\pm},$$

where

$$\kappa_n = \kappa + \frac{2\pi n}{d} \quad \text{and} \quad \zeta_n(k) = \begin{cases} \sqrt{k^2 - \kappa_n^2}, & |\kappa_n| \le k, \\ i\sqrt{\kappa_n^2 - k^2}, & |\kappa_n| > k. \end{cases}$$

# Three Configurations of Periodic Slits



- Normalization:  $\ell = 1$ .
- Three configurations of periodic slits:
  - (I)  $\varepsilon \ll d \sim \lambda \sim O(1)$ : diffraction regime.
- (II)  $\varepsilon \ll d \ll \lambda$ : homogenization regime I
- (III)  $\varepsilon \sim d \ll \lambda \sim O(1)$ : homogenization regime II



- Reduce to the first Brillouin zone:  $\kappa \in (-\pi/d, \pi/d]$ .
- Exterior Green's function in  $\Omega^{\pm}$ :  $g^{e}_{\sharp}(x,y) = g^{d}_{\sharp}(x,y) + g^{d}_{\sharp}(x',y)$ , where

$$g^{d}_{\sharp}(x,y) = -\frac{i}{2d} \sum_{n=-\infty}^{\infty} \frac{1}{\zeta_{n}(k)} e^{i\kappa_{n}(x_{1}-y_{1})+i\zeta_{n}(k)|x_{2}-y_{2}|},$$

and

$$\kappa_n = \kappa + \frac{2\pi n}{d} \quad \text{and} \quad \zeta_n(k) = \begin{cases} \sqrt{k^2 - \kappa_n^2}, & |\kappa_n| \le k, \\ i\sqrt{\kappa_n^2 - k^2}, & |\kappa_n| > k. \end{cases}$$

◆ロ ▶ ◆昼 ▶ ◆臣 ▶ ◆臣 ▶ ◆ 臣 ● 少々で

# Diffraction Regime: Integral Equation and Asymptotic Expansion



• Integral equation formulation over one reference period:

$$\begin{cases} & \int_{\Gamma_{\varepsilon}^{+}} g_{\sharp}^{\varepsilon}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} + \int_{\Gamma_{\varepsilon}^{+} \cup \Gamma_{\varepsilon}^{-}} g_{\varepsilon}^{i}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} = -(u^{i} + u^{r}), \quad \text{on } \Gamma_{\varepsilon}^{+}, \\ & \int_{\Gamma_{\varepsilon}^{-}} g_{\sharp}^{\varepsilon}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} + \int_{\Gamma_{\varepsilon}^{+} \cup \Gamma_{\varepsilon}^{-}} g_{\varepsilon}^{i}(x,y) \frac{\partial u_{\varepsilon}}{\partial v} ds_{y} = 0, \quad \text{on } \Gamma_{\varepsilon}^{-}. \end{cases}$$

• Boundary integral equation after scaling:

$$\begin{bmatrix} T^{e}_{\sharp} + T^{i} & \tilde{T}^{i} \\ \tilde{T}^{i} & T^{e}_{\sharp} + T^{i} \end{bmatrix} \begin{bmatrix} \varphi_{1} \\ \varphi_{2} \end{bmatrix} = \begin{bmatrix} f/\varepsilon \\ 0 \end{bmatrix}.$$

 $T^{e}_{\sharp}$  is the integral operator with kernel  $G^{e}_{\sharp,\varepsilon}$ :

$$G^{e}_{\sharp,\varepsilon}(X,Y) = \frac{1}{\pi} \left( \ln \varepsilon + \ln 2 + \ln \frac{\pi}{d} \right) + \frac{1}{2\pi} \sum_{n \neq 0} \frac{1}{|n|} - \frac{i}{d} \sum_{n = -\infty}^{\infty} \frac{1}{\zeta_n(k)} + \frac{1}{\pi} \ln |X - Y| + O(\varepsilon |X - Y|).$$

• Asymptotics of integral operators and the resonance condition can be obtained!

#### Diffraction Regime: Rayleigh Anomaly Frequencies

• Rayleigh anomaly frequencies:  $k = \kappa_n = \kappa + 2\pi n/d$  or  $\zeta_n = 0$  for some *n*.

Note that the scattered field

$$u_{\mathcal{E}}^{s}(x_{1},x_{2}) = \sum_{n=-\infty}^{\infty} u_{n}^{s,\pm} e^{i\kappa_{n}x_{1}\pm i\zeta_{n}x_{2}}, \quad \zeta_{n}(k) = \begin{cases} \sqrt{k^{2}-\kappa_{n}^{2}}, & |\kappa_{n}| \leq k, \\ i\sqrt{\kappa_{n}^{2}-k^{2}}, & |\kappa_{n}| > k. \end{cases}$$

Resonances away from the Rayleigh anomaly frequencies: consider the domain

$$D_{\kappa,\delta,M} := \mathbb{C} \setminus B_{\kappa,\delta} \cap \{z \mid |z| \le M\}, \quad \text{where } B_{\kappa,\delta} := \bigcup_{n = -\infty}^{\infty} B_{\delta}(\kappa + 2\pi n/d).$$

メ 伊 ト メ ヨ ト メ ヨ ト

# Diffraction Regime: Resonances and Eigenvalues

#### Theorem

For each  $\kappa \in (-\pi/d, \pi/d]$ , if  $m\pi \in D_{\kappa,\delta,M}$ , there exists a resonance or an eigenvalue  $k_m$  in the neighborhood of  $m\pi$ .

• If  $m\pi > |\kappa|$ ,  $k_m$  is a resonance. Otherwise,  $k_m$  is an eigenvalue.

• The following asymptotic expansion holds for  $k_m$  if  $m\varepsilon \ll 1$ :

$$k_m = m\pi + 2m\pi \left[\frac{1}{\pi}\varepsilon\ln\varepsilon + \left(\frac{1}{\alpha} + \gamma(m\pi,\kappa,d)\right)\varepsilon\right] + O(\varepsilon^2\ln^2\varepsilon),$$

Here 
$$\alpha = \langle K^{-1}1, 1 \rangle$$
,  $\gamma(k, \kappa, d) = \frac{1}{\pi} \left( 3\ln 2 + \ln \frac{\pi}{d} \right) + \left( \frac{1}{2\pi} \sum_{n \neq 0}^{\infty} \frac{1}{|n|} - \frac{i}{d} \sum_{n = -\infty}^{\infty} \frac{1}{\zeta_n(k)} \right)$ 



• Im  $\gamma(m\pi,\kappa,d) = -\frac{1}{d}\sum_{|\kappa_n| < m\pi} \frac{1}{\zeta_n(m\pi)} < 0$  if  $m\pi > |\kappa|$ ,

and the resonance has an imaginary part of  $O(\varepsilon)$ .

- Im  $\gamma(m\pi,\kappa,d) = 0$  if  $m\pi < |\kappa|$ .
- The eigenvalue occurs only if d < 1.
- The eigenmode u<sup>s</sup><sub>ε</sub> is a surface bound state (decaying exponetial away from the grating surface).

イロト イポト イヨト イヨト 二日

# Surface Bound State



#### Field Enhancement at Resonant Frequencies II



## In the slit $S_{\varepsilon}^{(0)}$

The wave field adopts the following expansion at the odd and even resonances respectively:

$$u_{\varepsilon}(x) = \frac{1}{\varepsilon} \cdot \frac{i}{\operatorname{Im} \gamma(m\pi, \kappa, d) \cdot k \sin(k/2)} \cdot \cos(k(x_2 - 1/2)) + O(\ln^2 \varepsilon)$$

and

$$u_{\varepsilon}(x) = -\frac{1}{\varepsilon} \cdot \frac{i}{\operatorname{Im} \gamma(m\pi, \kappa, d) \cdot k \cos(k/2)} \cdot \frac{\sin(k(x_2 - 1/2))}{\sin(k(x_2 - 1/2))} + O(\ln^2 \varepsilon).$$

## Homogenization Regime I. $\varepsilon \ll d \ll \lambda$



- No scattering resonance or eigenvalue exists if  $k \ll 1$  (or  $\lambda \gg 1$ ).
- If  $\varepsilon \ll 1$  and  $k = \varepsilon^{\sigma}$ , in the reference slit,

$$\begin{split} u_{\varepsilon}(x) &= \left(\frac{\alpha}{\varepsilon \cdot \lambda_{1}} + \frac{\alpha}{\varepsilon \cdot \lambda_{2}}\right) \cdot \frac{\cos(kx_{2})}{k \sin k} + \left(\frac{\alpha}{\varepsilon \cdot \lambda_{1}} - \frac{\alpha}{\varepsilon \cdot \lambda_{2}}\right) \cdot \frac{\cos(k(1-x_{2}))}{k \sin k} + H.O.T \\ &= \begin{cases} 2x_{2} + O(\varepsilon^{2\sigma}) + O(\varepsilon^{1-\sigma}) & \text{if } 0 < \sigma < 1, \\ 1 + id \cdot \cos\theta(2x_{2} - 1)\varepsilon^{\sigma-1} + O(\varepsilon^{\sigma+1}) + O(\varepsilon^{2(\sigma-1)}) & \text{if } \sigma > 1, \end{cases} \end{split}$$

• No magnetic enhancement is gained. However, the leading-order term has a slope of 2 and  $O(\varepsilon^{\sigma-1})$  respectively .

## Homogenization Regime I: Non-resonant Field Enhancement



#### Electric field enhancement

If  $\varepsilon \ll 1$  and  $k = \varepsilon^{\sigma}$ , then  $E_{\varepsilon} = [E_{\varepsilon,1}, E_{\varepsilon,2}, 0]$  in the reference slit, where

$$E_{\varepsilon,1} = \begin{cases} \frac{2i}{\sqrt{\tau_0/\mu_0}} \cdot \frac{1}{\varepsilon^{\sigma}} + H.O.T & \text{if } 0 < \sigma < 1, \\ \frac{d\cos\theta}{\sqrt{\tau_0/\mu_0}} \cdot \frac{1}{\varepsilon} + H.O.T & \text{if } \sigma > 1, \end{cases} \text{ and } E_{\varepsilon,2} \sim O(e^{-1/\varepsilon}).$$

▲ロ ▶ ▲ 圖 ▶ ▲ 画 ▶ ▲ 圖 ▶ ▲ 圖 ◆ � � �

## Homogenization Regime II: $\varepsilon \sim d \ll \lambda$



•  $\eta := \varepsilon/d$ , where  $0 < \eta < 1$ .

whe

 Asymptotic expansion of the scattering solution can be obtained, using the expansion for the periodic Green's function:

$$G^{e}_{\varepsilon}(X,Y) = \frac{1}{\pi}\ln 2 - \frac{i\eta}{\zeta\varepsilon} + \frac{1}{\pi}\ln|\sin(\pi\eta(X-Y))| + \frac{\kappa\eta}{\zeta}(X-Y) + O(\varepsilon),$$
  
re  $\kappa^{2} + \zeta^{2} = k^{2}.$ 

#### ・ロト・西ト・日下・ 日下 ろんの

#### Homogenization Regime II: "Surface Plasmon"



#### Theorem

There exist two groups of dispersion relations satisfying  $|\kappa| > k$ , and their leading

orders are: 
$$\kappa = k \sqrt{1 + \eta^2 \left(\frac{\sin k}{\cos k \pm 1}\right)^2}, \quad \eta = \varepsilon/d.$$

- The associated eigenmodes  $u_{\varepsilon}^{s}$  are surface bound states.
- The dispersion relations and surface bound states resemble the ones for surface plasmon polaritons in the dielectric-metal configuration.



# Homogenization Regime II: Total Transmission



- Scattering by an incident plane wave  $u^i = e^{i(\kappa x_1 \zeta(x_2 1))}$ , where  $\kappa = k \sin \theta$ ,  $\zeta = k \cos \theta$ , and  $|\kappa| < k$ .
- The leading orders of the reflection and transmission coefficients are

$$R_0 = \frac{i\tan k \cdot (\eta^2 - \cos^2 \theta)}{-i\tan k \cdot (\eta^2 + \cos^2 \theta)) + 2\eta \cos \theta}, \quad T_0 = \frac{2\cos \theta \cdot \eta}{-i\sin k \cdot (\eta^2 + \cos^2 \theta) + 2\cos \theta \cdot \eta \cos k}$$

• Total transmission is achieved when  $k = m\pi$  (Fabry-Perot resonance), and all frequencies for a special incident angle  $\theta$  such that  $\cos \theta = \eta$  (Brewster angle).





Field enhancement for PEC metals:

- Single slit: resonant and non-resonant enhancement effects.
- An array of slits: resonant and non-resonant enhancement effects, surface bound states, "surface plasmon", and total transmission.
- Asymptotics of resonances/eigenvalues are derived, and the enhanced wave modes are characterized.



- Multiscale problem: size of slit aperture δ, skin depth of metal δ<sub>m</sub>, thickness of slab d, and wavelength λ;
- The skin depth effect weakens the Fabry-Perot resoance, and induces small shifts of the FP resonance;
- The slit structure can excite plasmonic surface waves (plasmonic resonance) along the metal interface;
- The plasmonic resonance can interact with the FP resonance, an vice visa.

#### Numerical results



Figure: The transmittance T over the frequency band [0.5, 15] for various slit sizes.

- For numerical results, see "An integral equation method for numerical computation of scattering resonances in a narrow metallic slit", J. L and H. Z, submitted;
- Por theoretical results, coming soon.

3D subwavelength structures: quantitative analysis



Applications in sensing and control of light.

Thank you for your attention!